Model Name:

Elite Switched PDU

Elite Switched PDU provides remote manual control of the critical devices by clicking on a few buttons on the smart phone or computer webpage. Stop the problem device by cutting off the power to a specific outlet. By cycling the power off and restarting the device remotely, you save time and money by eliminating the need to send technicians to the root cause of the problem.

Managers can monitor the total power usage information of PDU from the remote end through the Internet to fully understand the power consumption of all the devices. Set up overload event alerts and notify managers via Email and TRAP, allowing managers to respond to crises in the shortest possible time to minimize disasters.

The PDU has environmental sensor ports that track climate information: temperature and humidity environment variables. The data is available from any web browser and is SNMP-compliant for easy tracking of critical data without the use of any external software.

Provide central management software, which can manage a large number of PDUs' power, temperature and humidity information. The database stores the power consumption information of the power strip and provides the history curve chart for the manager's reference.

Features:

System Function:

- Embedded system:
 Support 10/100M Ethernet interface, provides webpage and SNMP remote management.
- Local display information:
 Seven-segments can display current, IP address and temperature and humidity values.
- Multiple protocols:
 Support ICMP, ARP, IP, TCP, UDP, DHCP, HTTP,
 HTTPS, FTP, NTP, SNMP v1/2/3, TLS1.3, IPv4 and
 IPv6, Telnet, SSHv2
- Management Account Certification: Radius certification support.
- Multi-account management:
 Multi-group account management system. And provide three-tier permission management.
- IP filtering: Support IP filtering, improve network security mechanisms.
- Power record:
 Store up to 100000 power and event data.

- Remote firmware upgrade:
 Provides remote firmware upgrade mechanism.
- System operation message:
 Send the normal operation of the message automatically by trap.
- Hardware key definition:
 User-definable button function.
- Temperature unit conversion:
 Temperature units can choose Celsius or
 Fahrenheit
- System configuration restore: Support the output of the system settings, to easily deploy a large amount of the same model of PDU.
- Multilingual Support:
 Support Chinese, English, French, German,
 Spanish, Russian, Czech, Arabian, Persian.

Power Management:



REMOTE MONITOR

Remote Monitor

Remote monitoring PDU status by web and SNMP



REMOTE CONTROL

Remote Control

Remote per outlet on/off by web and SNMP.



CURRENT MEASUREMENT

Current Measurement

Measure PDU total current consumption.



MAIL NOTIFICATION

Mail Notification

Notify specified user by mail and SNMP when outlet action or current over threshold.



Threshold Sensing

User-definable warning and overload threshold value as the basis for alarm.



EVENT

Event Alert

When current exceeds the preset threshold, PDU will beep and LED will flash.



Power Sequence

User-definable power on/off sequence time.



Schedule Control

Timed & scheduled on/off/reboot control.



PING EVENT

Ping Event Control

When the specified IT device does not respond to PING, the output will perform a preset power action.



OVERLOAD

Overload Protection

When overload, circuit breaker will automatically trip to protect the safety of electricity.



Group Control

Set multiple outlets as a single group while controlling the power output.



CENTRAL MANAGEMENT

Central Management

Free centralized monitoring software, real-time monitoring of a large number of PDU, provide data records and history chart.



Event Reaction

Outlet action via pre-set event, including power, environment event and receiving trap from other device.



DETECTION

Environment Detection

Optional accessory probe to detect temperature and humidity.



KWH MEASUREMENT

kWh Measurement

Voltage, frequency, power factor, active power, apparent power and kWh measurement.



Circuit Breaker Detection

PDU can detect whether breaker is tripped due to the power event. Display and notify the manager of breaker status accordingly

Model Number:

WSC-2020Q-16N1







Specification

| Output | | Input | |
|--|---|--|--|
| Voltage Max. Current Outlet ON/OFF Ind. Circuit Ind. Overload Protection | 200-240 VAC 20 A (14) C13, (2) C19 (16) Green LED (1) Red LED | Voltage Frequency Max. Capacity Connection | 200-240 VAC 50/60Hz, full range 4800 VA L6-20P, power cord, 3m |
| Measurement | (1) 20A UL489 breaker | Other | |
| Current Voltage Active Power Apparent Power Frequency Power Factor kWh | +/- 1%+/-0.1A @0.2A ~ 32 A +/- 1% +/- 1V @80V~250V +/- 1% +/- 5W @50W~8000W +/- 1% @50VA~8000VA +/- 1% @50~65Hz +/- 1% @0.1~1.0 .001kWh~99999.999kWh, (+/- 1% @50W~8000W) kh=1.0 | ENET Connection ENV Connection Function Selection DHCP Ind. SSL Ind. Info. Display | (1) RJ45(2) RJ11(1) Button(1) Green LED(1) Blue LED4 digits of 7 Segments |
| Dimension/Weight | | Operation | |
| Net Size Net Weight Package Size Package Weight | 1245 x 56 x 80 mm 5.7 kg 1360 x 220 x 110 mm 6.9 kg | Operation Temp. Operation Humid. Storage Temp. Storage Humid. | 0 ~ 50°C 0% ~ 90% RH -20°C ~ 65°C 0% ~ 90% RH |
| Approval | | | |
| Certification Warranty | CE, FCC,ETL (UL62368-1) 2 years | | |

Package



Optional Accessory



Line Drawing

