Model Name: Elite Switched PDU Adv.

Elite Switched PDU provides remote manual control of the critical devices by clicking on a few buttons on the smart phone or computer webpage. Stop the problem device by cutting off the power to a specific outlet. By cycling the power off and restarting the device remotely, you save time and money by eliminating the need to send technicians to the root cause of the problem.

Managers can monitor the total power usage information of PDU from the remote end through the Internet to fully understand the power consumption of all the devices. Set up overload event alerts and notify managers via Email and TRAP, allowing managers to respond to crises in the shortest possible time to minimize disasters.

The PDU has environmental sensor ports that track climate information: temperature and humidity environment variables. The data is available from any web browser and is SNMP-compliant for easy tracking of critical data without the use of any external software.

Provide central management software, which can manage a large number of PDUs' power, temperature and humidity information. The database stores the power consumption information of the power strip and provides the history curve chart for the manager's reference.

It provides an advanced function which is to manage up to 8 PDUs by a single IP address. It means administrators can monitor and control multiple PDUs through one web interface.

Features:

System Function:

- Embedded system: Support 10/100M Ethernet interface, provides webpage and SNMP remote management.
- Local display information: OLED can display current, voltage, kWh, IP, temperature and humidity information.
- Multiple protocols: Support ICMP, ARP, IP, TCP, UDP, DHCP, HTTP, HTTPS, FTP, NTP, SNMP v1/2/3, TLS1.3, IPv4 and IPv6, Telnet, SSHv2
- Management Account Certification: Radius certification support.
- Multi-account management: Multi-group account management system. And provide three-tier permission management.
- IP filtering: Support IP filtering, improve network security mechanisms.
- Power record: Store up to 100000 power and event data.
- Daisy Chain:
 Support cascading management

- Remote firmware upgrade:
 Provides remote firmware upgrade mechanism.
- Heart beat notification: Send normal operation message automatically by trap.
- Hardware key definition: User-definable button function.
- Temperature unit conversion: Temperature units can choose Celsius or Fahrenheit
- System configuration restore: Support the output of the system settings, to easily deploy a large amount of the same model of PDU.
- Multilingual Support: Support Chinese, English, French, German, Spanish, Russian, Czech, Arabian, Persian.
- USB Option: Support external USB network card, support wireless network
- Hot-Swap: the replacement of network module without shutting down the PDU

Power Management:



Remote Monitor

Remote monitoring PDU status by web and SNMP



Current Measurement

Measure PDU total current consumption.

time.



Threshold Sensing

User-definable warning and overload threshold value as the basis for alarm.



Power Sequence User-definable power on/off sequence

AUTO PING PING EVENT

CONTROL

Ping Event Control

When the specified IT device does not respond to PING, the output will perform a preset power action.



Group Control

Set multiple outlets as a single group while controlling the power output.



Event Reaction

Outlet action via pre-set event, including power, environment event and receiving trap from other device.



kWh Measurement

Voltage, frequency, power factor, active power, apparent power and kWh measurement.





Remote Control

Remote per outlet on/off by web and SNMP.



Mail Notification

Notify specified user by mail and SNMP when outlet action or current over threshold.



Event Alert

When current exceeds the preset threshold, PDU will beep and LED will flash.









Overload Protection

When overload, circuit breaker will automatically trip to protect the safety of electricity.



Central Management

Free centralized monitoring software, real-time monitoring of a large number of PDU, provide data records and history chart.



Environment Measurement

Optional accessory probe to measure temperature and humidity.



Circuit Breaker Detection

PDU can detect whether breaker is tripped due to the power event. Display and notify the manager of breaker status accordingly





Model Number:

WSL-3020P-16N2







Output		Input	
Voltage Max. Current Outlet ON/OFF Ind. Overload Protection	200-240 VAC 30 A (14) C13, (2) C19 (24) Green LED (2) 20A UL489 breaker	Voltage Frequency Max. Capacity Connection Power Ind.	200-240 VAC 50/60Hz, full range 7200 VA L6-30P, power cord, 3m (1) Red LED
Measurement		Other	
Current Voltage Active Power Apparent Power Frequency Power Factor kWh	+/- 1%+/-0.1A @0.2A ~ 32 A +/- 1% +/- 1V @80V~250V +/- 1% +/- 5W @50W~8000W +/- 1% @50VA~8000VA +/- 1% @50~65Hz +/- 1% @0.1~1.0 .001kWh~99999.999kWh, (+/- 1% @50W~8000W) kh=1.0	ENET Connection ENV Connection Function Selection Daisy Chain WIFI Ready Info. Display	(1) RJ45 (2) RJ11 (1) Button (2) RJ22 (1) USB Monochrome OLED
Dimension/Weight		Operation	
Net Size Net Weight Package Size Package Weight	1245 x 56 x 80 mm 6.1 kg 1360 x 220 x 110 mm 7.1 kg	Operation Temp. Operation Humid. Storage Temp. Storage Humid.	0 ~ 50℃ 0% ~ 95% RH -20℃ ~ 65℃ 0% ~ 95% RH
Approval			
Certification Warranty	CE, FCC,ETL (UL62368-1) 2 years		

Package

No.	Description		
1	PDU 1 set		
2	Rack mount accessories 2 sets		
3	Software, manual, MIB by link below		



Optional Accessories

Model Number	Model Name
CPM-ENV-2	Temp./Humidity probe
STR-C14-B	C13 socket protection
STR-C20-B	C19 socket protection
CPM-USB-1	USB WIFI Dongle

Line Drawing



