## **Model Name:**

## Intelligent 4 DI/DO Manager

The manager provides DIDO function. Users can remotely connect any type of sensor, including smoke detection, water detection, flow detection, access control, proximity switches and other sensors to determine the environmental status. When the status changes, set event alarms and notify managers via e-mail and SNMP TRAP, so that managers can respond to crises in the shortest time to minimize disasters.

The manager also has a temperature and humidity sensor interface, which can add a set of sensors to track temperature and humidity data.

Provide management software, which can manage a large number of environmental managers at the same time, store data in the database, and provide historical curve charts for reference.

## Features:

## **System Function:**

- Embedded system:
   Support 10/100M Ethernet interface, provides webpage and SNMP remote management.
- Multiple protocols: Support ICMP, ARP, IP, TCP, UDP, DHCP, HTTP, HTTPS, FTP, NTP, SNMP v1/2/3, TLS1.3, IPv4 and IPv6, Telnet, SSHv2
- Management Account Certification: Radius certification support.
- Multi-account management:
   Multi-group account management system. And provide three-tier permission management.
- IP filtering: Support IP filtering, improve network security mechanisms.
- Power record:
   Store up to 100000 power and event data.

- Remote firmware upgrade:
   Provides remote firmware upgrade mechanism.
- System operation message:
   Send the normal operation of the message automatically by trap.
- Hardware key definition:
   User-definable button function.
- Temperature unit conversion:
   Temperature units can choose Celsius or
   Fahrenheit
- System configuration restore: Support the output of the system settings, to easily deploy a large amount of the same model of PDU.
- Multilingual Support:
   Support Chinese, English, French, German,
   Spanish, Russian, Czech, Arabian, Persian.

## **Power Management:**



REMOTE MONITOR

### **Remote Monitor**

Remote monitoring device status by web and SNMP



## **Remote Control**

Remote DO on/off by web and SNMP.



Digital I/O

## Digital I/O

Connect various sensors. Support web pages to set various actions.



## **Mail Notification**

**Event Reaction** 

Notify specified user by mail and SNMP when DO action or current over threshold.



### **Schedule Control**

Timed & scheduled on/off/reboot control.



DO action via pre-set event, including power, environment event and receiving trap from other device.



## **Ping Event Control**

When the specified IT device does not respond to PING, the output will perform a preset power action.



### **Environment Detection**

Optional accessory probe to detect temperature and humidity.



## **Power Sequence**

User-definable DO on/off sequence time.

## **Model Number:**

## **IOT-IO-04**



# **Specification**

Specification				
Input		Other		
Voltage	100VAC-240VAC	<b>ENET Connection</b>	(1) RJ45	
Connection	C14 Inlet	<b>ENV Connection</b>	(2) RJ11	
Power Status	(1) Red LED	<b>Function Selection</b>	(1) Button	
		DHCP Ind.	(1) Green LED	
		SSL Ind.	(1) Blue LED	
		Info. Display	4 digits of 7 Segments	
DI		DO		
Type: Dry contact 1 set of 4-way terminal block. Connection: 0.5 to 1.5 mm²/ 28 to 14AWG Close status: Impedance less than 50 ohms Open status: Impedance greater than 50 ohms		Connection: 0.5 to 2. Range : Contact Oper Rated load:16A 240V	Type: Relay 1 set of 4-way terminal block. Connection: 0.5 to 2.5 mm²/24 to 12 AWG Range: Contact Open(off) or Close (on) Rated load:16A 240VAC / 16A 24Vdc Max. switching current: 16A	

Dimension/Weight	Operation
	Max. switching voltage: 250VAC Max. switching capacity: 4000VA
	Max. switching current: 16A

Net Size	210 x110 x 56 mm	
Net Weight	1 kg	
Package Size	TBD	
Package Weight	TBD	

Approval	
Warranty	2 vears

Operation Temp.  $0 \sim 50^{\circ}\mathbb{C}$ Operation Humid.  $0\% \sim 90\%$  RH

Storage Temp.  $-20^{\circ}\mathbb{C} \sim 65^{\circ}\mathbb{C}$ Storage Humid.  $0\% \sim 90\%$  RH

# **Package**

No.	Description	
1	PDU 1 set	
2	Model number: IOT-IO-04A	Model number: IOT-IO-04J
	C13 to 5-15P, power cord 1.8m	Power cord, C13 to C14, 1.8 m
3	Manual, MIB by link below	



# **Line Drawing**









